






1	General information	Supplier's name or trade mark	INSPIRE		
2		Supplier's address	ADEO Services, 135 rue Sadi Carnot - CS0001, 59790 RONCHIN		
3		Model Identifier - Luminaire Supplier reference	6401004012		
4		Light sources maker model	0743982701		
5		Date of placement on the market	2021/11/1		
6	Type of light source:	Lighting technology used:	LED		
7		Light source cap type (or other electric interface)	GX53		
8		Non-directional (NDLS) or directional (DLS):	NDLS		
9		Mains (MLS) or non-mains (NMLS):	MLS		
10		Connected light source (CLS):	no		
11		Colour-tuneable light source:	no		
12		Envelope:	no		
13		High luminance light source:	no		
14		Anti-glare shield:	no		
15		Dimmable:	no		
16	General product parameters:	Energy consumption in on-mode (kWh/1000 h)	6	kWh/1000h	
17		Energy efficiency class	F		
18		Useful luminous flux ( $\Phi_{use}$ ), indicating if it refers to the flux in a sphere (360°), in a wide cone (120°) or in a narrow cone (90°), expressed in Lm	600LM	360	
19		Correlated colour type	single value		
20		Correlated colour temperature, rounded to the nearest 100 K, or the range of correlated colour temperatures, rounded to the nearest 100 K, that can be set	2700	K	
21		On-mode power ( $P_{on}$ ), expressed in W	-	W	
22		Standby power ( $P_{sb}$ ), expressed in W and rounded to the second decimal	0.00	W	
23		Networked standby power ( $P_{net}$ ) for CLS, expressed in W and rounded to the second decimal	0.00	W	
24		Colour rendering index, rounded to the nearest integer, or the range of CRI-values that can be set	80		
25		Outer dimensions without separate control gear, lighting control parts and nonlighting control parts, if any (millimetre)			
26		Height (mm)	25.00	mm	
27		Width (mm)	75.00	mm	
28		Depth (mm)	75.00	mm	
29		Spectral power distribution in the range 250 nm to 800 nm, at full-load (insert picture of the spectral power distribution)	6401004012-spectral power distribution.jpeg 		
30		Claim of equivalent power	yes		
31	If yes, equivalent power (W)	48	W		
32	Chromaticity coordinates (x and y)	0.463;0.420			
33	Parameters for directional light sources:	Peak luminous intensity (cd)	-		
34		Beam angle in degrees (no decimal), or the range of beam angles that can be set	-		
35	Parameters for LED and OLED light sources:	R9 colour rendering index value	5		
36		Survival factor rounded to the second decimal (>0.xx)	0.90		
37		Lumen maintenance factor rounded to the second decimal (>0.xx)	0.96		
38	Parameters for LED and OLED mains lights sources:	displacement factor (cos $\phi_1$ ) rounded to the second decimal	0.93		
39		Colour consistency in McAdam ellipses	6		
40		Claims that an LED light source replaces a fluorescent light source without integrated ballast of a particular wattage.	-		
41		If yes then replacement claim (W)	-	W	
42		Flicker metric (Pst LM)	0.0		
43	Stroboscopic effect metric (SVM)	0.0			
44	Technical documentation name (in case of light source product)				
45	Light source removing instruction name (in case of containing product)		6401004012-Light source removing instruction.pdf		

1	General information	Supplier's name or trade mark	INSPIRE
2		Supplier's address	ADEO Services, 135 rue Sadi Carnot - CS0001, 59790 RONCHIN
3		Model Identifier - Luminaire Supplier reference	6401004012
4		Light sources maker model	743982701

Instructions on how to remove lighting control parts and/or non-lighting parts, if any, or how to switch them off or minimise their power consumption during light source testing

	Explanation of the step	Pictures	Tools
Step 1	Use an Allen key to open the cover		Allen hex key
Step 2	take out the glass		
Step 3	Unscrew the bulb		
Step 4			
Step 5			
Step 6			
Step 7			
Step 8			
Step 9			
Step 10			