







		PRODUCT INFORMATION SHEET (ANNEX 5)		Creation date (dd/mm/yyyy) :	09/02/2022	
				Last update date (dd/mm/yyyy) :	09/02/2022	
1	General information	Supplier's name or trade mark				
2		Supplier's address	ADEO Services, 135 rue Sadi Carnot – CS00001, 59790 RONCHIN			
3		Model Identifier – Luminaire Supplier reference	W210525102			
4		Light sources maker model	DLB-0370-B			
5		Date of placement on the market	09/02/2022			
6	Type of light source:	Lighting technology used:	LED			
7		Light source cap type (or other electric interface)	lead wire			
8		Non-directional (NDLS) or directional (DLS):	NDLS			
9		Mains (MLS) or non-mains (NMLS):	NMLS			
10		Connected light source (CLS):	no			
11		Colour-tuneable light source:	no			
12		Envelope:	no			
13		High luminance light source:	no			
14		Anti-glare shield:	no			
15	Dimmable:	no				
16	General product parameters:	Energy consumption in on-mode (kWh/1000 h)			4 kWh/1000h	
17		Energy efficiency class	E			
18		Useful luminous flux (Φ_{use}), indicating if it refers to the flux in a sphere (360°), in a wide cone (120°) or in a narrow cone (90°),	510		360	
19		Correlated colour type	single value			
20		Correlated colour temperature, rounded to the nearest 100 K, or the range of correlated colour temperatures, rounded to the nearest 100 K,	3000 K			
21		On-mode power (P_{on}), expressed in W and rounded to the first decimal	3.5	W		
22		Standby power (P_{sb}), expressed in W and rounded to the second decimal	0.00	W		
23		Networked standby power (P_{net}) for CLS, expressed in W and rounded to the second decimal	0.00	W		
24		Colour rendering index, rounded to the nearest integer, or the range of CRI-values that can be set	80			
25		Outer dimensions without separate control gear, lighting control parts and nonlighting control parts, if any (millimetre)				
26		Height (mm)			mm	
27		Width (mm)	25.00			mm
28		Depth (mm)			mm	
29		Spectral power distribution in the range 250 nm to 800 nm, at full-load (insert picture of the spectral power distribution + name of picture+extension (.jpeg)	W210525102_spectral power distribution 			
30		Claim of equivalent power	yes			
31		If yes, equivalent power (W)	42	W		
32		Chromaticity coordinates (x and y)	X=0.437, Y=0.399			
33	Parameters for directional light sources:	Peak luminous intensity (cd)			cd	
34		Beam angle in degrees (no decimal), or the range of beam angles that can be set			Degrees	
35	Parameter for LED and OLED light sources:	R9 colour rendering index value	1			
36		Survival factor rounded to the second decimal ($>0.xx$)	0.90			
37		Lumen maintenance factor rounded to the second decimal ($>0.xx$)	0.96			
38	Parameters for LED and OLED mains lights sources:	displacement factor ($\cos \phi_1$) rounded to the second decimal	0.00			
39		Colour consistency in McAdam ellipses	1.7			
40		Claims that an LED light source replaces a fluorescent light source without integrated ballast of a particular wattage.	-			
41		If yes then replacement claim (W) (no decimal)	0.0	W		
42		Flicker metric (Pst LM) rounded to the first decimal	0.0			
43		Stroboscopic effect metric (SVM) rounded to the first decimal	0.1			
44	Technical documentation name (in case of light source product)					
45	Light source removing instruction name (in case of containing product)		W210525102_light source remove instruction.pdf			

LIGHT SOURCE REMOVING INSTRUCTION			Creation date (dd/mm/yyyy) :	21/04/2022
			Last update date (dd/mm/yyyy) :	21/04/2022
1	General information	Supplier's name or trade mark	INSPIRE	
2		Supplier's address	ADEO Services, 135 rue Sadi Carnot - CS0001, 59790 RONCHIN	
3		Model Identifier - Luminaire Supplier reference	#210525102	
4		Light sources maker model	DLB-0370-B	

Instructions on how to remove lighting control parts and/or non-lighting parts, if any, or how to switch them off or minimise their power consumption during light source testing

	Explanation of the step	Pictures	Tools
Step 1	Turn off the power, remove the bracket		screwdriver
Step 2	Use a screwdriver to remove the screw and light source cover		screwdriver
Step 3	Remove the bracket of aluminum base		by hand
Step 4	Remove the terminal block, and note the wiring method for wiring during installation		by hand
Step 5	Remove the damaged light source and replace it with a new one		by hand
Step 6	Put the bracket of aluminum base and light source cover back		screwdriver
Step 7	Lights up after installation		by hand