

# Lexman



**5** GUARANTEE  
**YEARS\***

EAN CODE : 3276007463774



Traduit des instructions originales / Traducido de las instrucciones originales / Traducido das instruções originais / Tradotto dalle istruzioni originali / Μετάφραση των αρχικών οδηγιών / Tłumaczenie z oryginalnych instrukcji / Переклад оригінальної інструкції / Traduceti instrucțiunile originale / Translated from original instructions.

- FR Manuel d'utilisation.
- ES Manual de utilización.
- PT Manual de utilização.
- IT Manuale per l'uso.
- EL Εγχειρίδιο χρήσης.
- PL Instrukcja obsługi.
- UA Керівництво з експлуатації.
- RO Manual de utilizare.
- EN Socket Tester User guide.

# Safety information

EN

**READ ALL OPERATING INSTRUCTIONS BEFORE USE**

## Warning :

Use extreme caution when testing live electrical circuits due to risk of injury from electric shock. This product assumes basic knowledge of electricity on the part of the user and is not responsible for any or damages due to improper use of this tester.

Observe and follow all standard industry safety rules and local electrical codes. When necessary call a qualified electrician to troubleshoot and repair the defective.

# Specifications

- Operating ranges AC 230V ( $\pm 10\%$ ), 50Hz~60Hz.

## Operation

- Plug the tester into any 230V ( $\pm 10\%$ ) standard socket.
- View the indications on the tester and match with the cart on the tester.
- If the tester indicates a wiring problem then turn off all power to the socket and repair wiring.
- Restore power to the socket and retest.



	RED	RED	RED	LX-M-300	
L>	OK, Phase on the right side	○	●	●	✓
L<	OK, Phase on the left side	●	●	○	✓
PE	Ground missing	○	●	○	✓
⌘	Phase missing	○	○	○	✓
N	Neutral missing	○	○	●	✓
N	Neutral missing	●	○	○	✓
L<>PE	Phase/Ground inverted	●	○	●	✓
L<>PE&PE	Phase /Ground inverted and Ground missing	●	●	●	✓
Socket Rated Voltage		250VAC		✓	
Socket Rated Current				10A	
回 :Double Insulated				✓	
CE				✓	
Pollution Degree		2		✓	
Operating Temperature		0°C~40°C		✓	
Storage		-10°C~50°C		✓	
Humidity		<75%		✓	
Altitude		2000m		✓	
This Unit Will Not Detect Earth Neutral Reverse				✓	
	Do not discard this product as an unclassified municipal waste, but put it into a fixed cell recycle bin for disposal.			✓	

○ LED OFF    ● LED ON



## Notice

- All appliances or equipment on the circuit being tested should be unplugged to help avoid erroneous readings.
- No a comprehensive diagnostic instrument but a simple instrument to detect nearly all probable common improper wiring conditions.
- Repair all indicated problems to a qualified electrician.
- Will not indicate quality of ground.
- Will not detect a combination of defects.
- Will not indicate reversal of grounded and grounding conductors.
- Check for correct wiring of socket and all remotely connected socket on the branch circuit.

## Cleaning Requirement :

Clean it with a cloth dampened with water.  
Notes : Resume its use only when it is completely dried out after it is cleaned.

# Lexman



Electrical products must not be disposed of with domestic waste. They must be taken to a communal collecting point for environmentally friendly disposal in accordance with local regulations. Contact your local authorities or stockist for advice on recycling. The packaging material is recyclable. Dispose of the packaging in an environmentally friendly manner and make it available for the recyclable material collection-service.

Don't throw batteries or out of order products with the household waste (garbage). The dangerous substances that they are likely to include may harm health or the environment. Make your retailer take back these products or use the selective collect of garbage proposed by your city.

FR

ADEO Services -  
135 Rue Sadi Carnot - CS 00001  
59790 RONCHIN - France

UA

ТОВ «Леруа Мерлен Україна»,  
вул. Полярна 17а, м. Київ 04201,  
Україна



\* Garantie 5 ans  
Garantía 5 años  
Garantia 5 anos  
Garanzia 5 anni  
5 έτη εγγύηση  
5 lata gwarancji  
Гарантія 5 роки  
5 ani garanție  
5-Year warranty



Made in CHINA